


# Universal Receiver STAR™250-433

## Access control receiver



- Universal receiver with antenna
- Rapid Learn™ feature programs multiple remote controls in seconds
- User-friendly programming technology makes it easy to add, block and delete up to 250 remote controls individually
- Ideal for gated communities, parking lots and garages
- Compatible with Chamberlain™, billion code, rolling code and keyless entry technologies
- 433.92 MHz
- Duplicate memory module may be removed for programming additional receivers or for safe back-up storage



### STAR™250-433

#### specifications:

Supply voltage:	12-24 volts AC or DC
Operating current:	250mA maximum
Oper. temp. range:	-40°C to +65°C
Frequency:	433.92MHz
Relay contact rating:	1 amp @ 24 volts AC or DC
Warranty:	2 years

### STAR™250-433 optional accessories

CGI part number	Description
041A2743X	Watertight box field install kit
86LM	Antenna extension kit
23024E	Transformer 230V/24V/AC

### STAR™250-433

#### compatible remote controls:

Billion Code	Rolling Code
4330E	94330E
4332E	94333E
4333E	94335E
4335E	
Keypads	Keypads
747E	9747E

